

PIR LIGHT SWITCHS

A-ES3



A-ES3 : 360° Stand Alone Type Motion sensor is a fully automatic indoor and outdoor security/courtesy light controller capable of controlling up to 1000W incandescent or 30W x 10 fluorescent of lighting. At night, the built in passive infrared (PIR) motion sensor turns on the connected lighting system when it detects motion in its coverage area. During the day, the built in photocell sensor saves electricity by deactivating the lights.

An adjustable time lets you select how long the light stays on after activation. The LITE adjustment determine at what light level the lighting system will start operating when you set the motion sensor to automatic mode.

SPECIFICATIONS

Power Requirement	: 230V AC 50Hz
Lighting Load	: Max.1500W incandescent bulb or Max. 300W fluorescent lamp
Detection Angle	: 360° around
Detection Distance	: Max. 5 Meters in radius at 10ft Height
Time Adjustment	: From 10 ± 5 seconds to 4 ± 1 minutes adjustable
Protection Class	: IP 20

APPLICATION AREA

Car Park , Corridor, Dining Area, Individual Cabins, Large Cabins, Lift Lobby, Lifts, Living Room, Lobbies, Meeting Rooms, Pantry, Reception Areas, Rest Room, Small Offices, Stairways, Stores